

iSwitch 402UC Rx API Commands

V1.0

Parameters	Value
Baud Rate	115200 bps
Data bits	8 bits
Parity	None
Stop bits	1 bit
Flow control	None

No.	Description	Command	Example
1	Select input for RX	Command: SWITCH prm <CR><LF> prm: HDBT , HDMI Return: SWITCH prm <CR><LF>	Command: SWITCH HDMI <CR><LF> Return: SWITCH HDMI <CR><LF>
2	Upgrade ARM	Command: UPG ARM <CR><LF> Return: UPG ARM <CR><LF>	Command: UPG ARM <CR><LF> Return: UPG ARM <CR><LF>
3	REBOOT	Command: REBOOT <CR><LF>	Command: REBOOT <CR><LF>

		Return: REBOOT <CR><LF>	Return: REBOOT <CR><LF>
4	Get firmware version	Command: GET VER <CR><LF> Return: VER XXX <CR><LF>	Command: GET VER<CR><LF> Return: VER 1.5 <CR><LF>